

Specification				
Part No.	InduSTance 1 (Ω)	Percent Tolerance	RDC ² Max (Ω)	IDC Max (MA)
FBM 0603 PT 110 S	11 @ 100 MHZ	S	0.02	4000
FBM 0603 PT 250 S	25 @ 100 MHZ	S	0.03	3000
FBM 0603 PT 400 S	40 @ 100 MHZ	S	0.04	3000
FBM 0603 PT 600 S	60 @ 100 MHZ	S	0.04	3000
FBM 0603 PT 121 S	120 @ 100 MHZ	S	0.05	2500
FBM 0603 PT 301 S	300 @ 100 MHZ	S	0.10	2000
FBM 0603 PT 501 S	500 @ 100 MHZ	S	0.15	1500
FBM 0603 PT 601 S	600 @ 100 MHZ	S	0.20	1000
FBM 0603 PT 102 S	1000 @ 100 MHZ	S	0.25	800
FBM 0805 PT 110 S	11 @ 100 MHZ	S	0.01	6000
FBM 0805 PT 170 S	17 @ 100 MHZ	S	0.02	5000
FBM 0805 PT 30 S	30 @ 100 MHZ	S	0.02	4000
FBM 0805 PT 500 S	50 @ 100 MHZ	S	0.03	3000
FBM 0805 PT 600 S	60 @ 100 MHZ	S	0.03	3000
FBM 0805 PT 800 S	80 @ 100 MHZ	S	0.04	3000
FBM 0805 PT 121 S	120 @ 100 MHZ	S	0.04	3000
FBM 0805 PT 201 S	200 @ 100 MHZ	S	0.05	2500
FBM 0805 PT 301 S	300 @ 100 MHZ	S	0.08	2000
FBM 0805 PT 601 S	600 @ 100 MHZ	S	0.10	2000
FBM 0805 PT 102 S	1000 @ 100 MHZ	S	0.12	1500
FBM 1206 PT 190 S	19 @ 100 MHZ	S	0.02	6000
FBM 1206 PT 320 S	32 @ 100 MHZ	S	0.02	4000
FBM 1206 PT 600 S	60 @ 100 MHZ	S	0.02	4000
FBM 1206 PT 800 S	80 @ 100 MHZ	S	0.03	3000
FBM 1206 PT 101 S	100 @ 100 MHZ	S	0.03	2500
FBM 1206 PT 301 S	300 @ 100 MHZ	S	0.06	2000
FBM 1206 PT 601 S	600 @ 100 MHZ	S	0.10	1800
FBM 1206 PT 102 S	1000 @ 100 MHZ	S	0.15	1200
FBM 1206 PT 122 S	1200 @ 100 MHZ	S	0.18	1000
FBM 1206 PT 152 S	1500 @ 100 MHZ	S	0.20	800
FBM 1210 PT 600 S	60 @ 100 MHZ	S	0.03	4000
FBM 1210 PT 900 S	90 @ 100 MHZ	S	0.03	3000
FBM 1806 PT 500 S	50 @ 100 MHZ	S	0.02	6000
FBM 1806 PT 600 S	60 @ 100 MHZ	S	0.02	5000
FBM 1806 PT 800 S	80 @ 100 MHZ	S	0.03	4000
FBM 1806 PT 151 S	150 @ 100 MHZ	S	0.10	2000
FBM 1812 PT 700 S	70 @ 100 MHZ	S	0.03	6000
FBM 1812 PT 121 S	120 @ 100 MHZ	S	0.03	4000

1. InduSTance is measured in HP-4286A LCR meter with HP-16192 fixture.

4. RDC is measured in HP-4338B milliohmmeter.
5. For 15 °C Rise.